

Pairing

Stormy 9000 Wireless Remote to the Dual Channel Receiver

Start by turning on the Wireless Remote:

Hold down the High House button on the remote. You will see the 2 LEDs on the remote flash back and forth for 5 sec. until both lights stop flashing. When the lights stop flashing immediately release the High House button.

Is the Dual Channel Receiver powered up?

Be sure the receiver has power. You can do that by looking inside the clear casing at the receiver board. You should see a solid green light. (may be faint in the sun)

Putting the Receiver into Pairing Mode:

Now that the Wireless Remote and Receiver are powered up you can start pairing.

Be sure to have the Wireless Remote with you when you are pairing.

Locate the button on the side of the Receiver.

Hold the button down until you see 2 LEDs flashing red back and forth on the receiver.

Now that the LEDs are flashing back and forth you can let go of the button.

Press the High House Button on the Wireless Remote once. When you do that the 2 red LEDs on the Receiver board will flash rapidly and then stop flashing after exposing only the green LED.

Pairing Test:

You are ready for testing.

Ensure that everyone is in a safe zone.

Press the High, Low and Doubles button on the Stormy 9000 Wireless Remote to be sure you are getting the desired results.